

---

Slotted trunkings  
U23X · Colour grey



77








---







Useful cross-sections

# Useful cross-sections (mm<sup>2</sup>)

## Recommended cable capacities

Part no.		Sizes (mm)							
Grey RAL 7030		18x20	25x20	33x30	42x20	42x30	42x43	42x60	
		234	322	728	586	940	1460	2112	
Cables V250 Number of cables (Filling ratio 1.5)*	0.5 mm <sup>2</sup>	43	53	116	96	154	237	346	
	0.75 mm <sup>2</sup>	28	35	77	63	102	157	229	
Cables H05/07 V-K Number of cables (Filling ratio 1.5)*	1 mm <sup>2</sup>	18	23	50	41	66	102	150	
	1.5 mm <sup>2</sup>	14	17	37	30	49	75	110	
	2.5 mm <sup>2</sup>	9	12	26	21	34	52	76	
Part no.		Sizes (mm)							
Grey / Blue RAL 7030 / RAL 5012		60x20	60x30	60x43	60x60	60x80	60x100	60x120	
		870	1387	2137	3092	4225	5362	6380	
Cables H05/07 V-K Number of cables (Filling ratio 1.5)*	1 mm <sup>2</sup>	62	98	150	219	299	384	450	
	1.5 mm <sup>2</sup>	45	72	111	161	220	283	331	
	2.5 mm <sup>2</sup>	32	50	77	112	153	196	230	
	4 mm <sup>2</sup>	25	40	61	89	122	157	184	
	6 mm <sup>2</sup>	14	23	35	51	70	90	106	

Part no.		Sizes (mm)						
RAL 7030 / RAL 5012		80x30	80x43	80x60	80x80	80x100	80x120	
		 1865	 2874	 4128	 5630	 7177	 8572	
Cables H05/07 V-K Number of cables (Filling ratio 1.5)*	1 mm <sup>2</sup>	132	203	291	399	504	606	
	1.5 mm <sup>2</sup>	97	149	215	293	371	446	
	2.5 mm <sup>2</sup>	68	104	149	204	258	309	
	4 mm <sup>2</sup>	54	83	118	162	206	247	
	6 mm <sup>2</sup>	31	47	68	92	118	142	

Part no.		Sizes (mm)				
RAL 7030		100x43	100x60	100x80	100x100	100x150
		 3585	 5179	 7110	 9000	 13450
Cables H05/07 V-K Number of cables (Filling ratio 1.5)*	1 mm <sup>2</sup>	253	366	502	633	994
	1.5 mm <sup>2</sup>	186	271	369	465	732
	2.5 mm <sup>2</sup>	129	188	257	324	508
	4 mm <sup>2</sup>	103	149	204	258	402
	6 mm <sup>2</sup>	59	85	117	148	201

\* Note: For other types of cables, the necessary section results from the application of the following formula:  
Section = Cable section x nr. cables x 1.5.