














Kanał grzebieniowy
U43X bezhalogenowy
• Kolor szary








88






Rozmiary przekrojów użytkowych

Rozmiary przekrojów użytkowych (mm²)

Rozmiary (mm)		25x20	33x30	40x20	42x30	42x43	42x60
Nr art.	Jasnoszary RAL 7035	25.20.88	30.30.88	40.20.88	40.30.88	40.40.88	40.60.88
		 322	 728	 586	 940	 1460	 2112
Przewody V250 Liczba przewodów (Wskaźnik wypełnienia 1,5)*	0,5 mm ²	53	116	96	154	237	346
	0,75 mm ²	35	77	63	102	157	229
Przewody H05/07 V-K Liczba przewodów (Wskaźnik wypełnienia 1,5)*	1 mm ²	23	50	41	66	102	150
	1,5 mm ²	17	37	30	49	75	110
	2,5 mm ²	12	26	21	34	52	76

Rozmiary (mm)		60x30	60x43	60x60	60x80	60x120
Nr art.	Jasnoszary RAL 7035	60.30.88	60.40.88	60.60.88	60.80.88	60.120.88
		 1387	 2137	 3092	 4225	 6380
Przewody H05/07 V-K Liczba przewodów (Wskaźnik wypełnienia 1,5)*	1 mm ²	98	150	219	299	450
	1,5 mm ²	72	111	161	220	331
	2,5 mm ²	50	77	112	153	230
	4 mm ²	40	61	89	122	184
	6 mm ²	23	35	51	70	106

Rozmiary (mm)		80x30	80x43	80x60	80x80	80x100	80x120
Nr art.	Jasnoszary RAL 7035	80.30.88	80.40.88	80.60.88	80.80.88	80.100.88	80.120.88
		 1865	 2874	 4128	 5630	 7177	 8572
Przewody H05/07 V-K Liczba przewodów (Wskaźnik wypełnienia 1,5)*	1 mm ²	132	203	291	399	504	606
	1,5 mm ²	97	149	215	293	371	446
	2,5 mm ²	68	104	149	204	258	309
	4 mm ²	54	83	118	162	206	247
	6 mm ²	31	47	68	92	118	142

Rozmiary (mm)		100x43	100x60	100x80	100x100
Nr art.	Jasnoszary RAL 7035	100.40.88	100.60.88	100.80.88	100.100.88
		 3585	 5179	 7110	 9000
Przewody H05/07 V-K Liczba przewodów (Wskaźnik wypełnienia 1,5)*	1 mm ²	253	366	502	633
	1,5 mm ²	186	271	369	465
	2,5 mm ²	129	188	257	324
	4 mm ²	103	149	204	258
	6 mm ²	59	85	117	148

* Uwaga! W przypadku innych typów przewodów wymagany przekrój wynika z zastosowania następującego wzoru: Przekrój = przekrój przewodu × liczba przewodów × 1,5.